

| Rating | Model | Engine |
|-------------------------|---------|-------------------------------------|
| 5.0KVA Petrol Generator | 5000HMS | HONDA The Power of Dreams |

| GENERATOR SPECIFICATION | |
|-------------------------|----------------------------|
| Frequency | 50Hz |
| Phase | Single |
| Voltage | 230/115 |
| Power | 5.0kVA / 4.0KW |
| Alternator | NSM K100F |
| Type | Brushless Maintenance Free |
| Regulation | Mechanical |
| Protection Class | IP23 |
| Insulation Class | H |
| Fuel tank capacity | 6.0 Litres |
| Autonomy 75% load | 3.5hr |
| LWA | 96 |
| DBA @ 7M | 71 |

| ENGINE SPECIFICATION | |
|----------------------------|-----------------|
| Engine | Honda GX270 |
| Emissions | N/A |
| Distribution | O.H.V. |
| Cylinders | 1 |
| Cooling | Air |
| Start | Recoil |
| Fuel | Petrol unleaded |
| Rpm | 3000 |
| Oil Capacity (L) | 1.1 |
| Oil Alert/Low Oil Shutdown | Yes |

3 Year Engine Warranty (Limited)



| OPTIONS |
|-----------------------------------|
| Single Voltage |
| LPG Conversion |
| Electric Start |
| Long Run Tank (Metal) |
| Trolley Kit |
| AVR (Automatic Voltage Regulator) |



| DIMENSIONS (mm) | | | |
|-----------------|-------|--------|-----------|
| Length | Width | Height | Weight KG |
| 690 | 480 | 540 | 59 |

| CONTROL BOX (METAL) |
|--|
| Push Button MCB Overload protection |
| 2 x 230V 16A BS4343 Sockets |
| 1 x 115V 16A 1 x 115V 32A BS4343 Sockets |
| Voltage Selector Switch |

Stephill Generators Ltd reserve the right to change any of the characteristics stated without notice, in a constant effort to improve the quality of its product

Stephill Generators Ltd
Wallis Close
Park Farm South
Wellingborough
Northants
NN8 6AG

Phone : :+44 (0)1933 677911
Fax : :+44 (0)1933 677916
E-mail : info@stephill-generators.co.uk
Web : www.stephill-generators.co.uk